

AUTOMATIC BATTERY CHARGER FOR 6/12/24V SEALED LEAD-ACID BATTERY

IMPORTANT SAFETY INSTRUCTIONS:

1. Before charging, read instruction.
2. This charger is intended for use with Lead Acid rechargeable batteries only. Attempting to charge other types of batteries may cause personal injury and damage to the charger.
3. Do not expose charger to rain or moisture. For indoor use only.
4. Remove from mains when not in use.
5. Never use an extension cord or any attachment not recommended by manufacturer, otherwise this may result in a risk of fire, electric shock or injury to persons.
6. Do not operate the charger if it has been subjected to shock or damage. Take it to a qualified serviceman for repair.
7. Do not disassemble the charger. Incorrect reassemble may result in a risk of electric shock or fire.
8. Unplug the charger from outlet before attempting any maintenance or cleaning.
9. This charger is intended to be correctly orientated in a vertical or floor mount position.
10. During charging, the battery must be placed in a well ventilated area.
11. This appliance is not intended for use by persons (including children) with reduced physical, sensory or mental capabilities, or lack of experience and knowledge, unless they have been given supervision or instruction concerning use of the appliance by a person responsible for their safety.
12. Children should be supervised to ensure that they do not play with the appliance.

SPECIFICATION:

Input: 100-240VAC 50/60Hz

Output: 6V/ 12V/ 24V DC 1.2A

Battery Type: 6V 8-12Ah, 12V 8-12Ah, 24V 8-12Ah
Lead Acid rechargeable battery.

No. of battery: One battery per charge

OPERATING INSTRUCTIONS:

1. Connect the charger's clips to the battery: Red pin to positive(+) terminal, Black pin to negative(-) terminal. Do not allow clips to touch each other.
2. This charger features voltage auto detect technology and will automatically adjust to accommodate either a 6V, 12V or 24V rechargeable lead acid battery. The LED indicates the battery charging status.
 - **Red LED lights on** – proper charging;
 - **Green LED lights on** – Battery gets fully charged and ready for use
 - **Flashing Red LED**– Short circuit, reverse polarity or battery voltage is too low to charge
3. The charging time for 6V/12V/24V 12Ah lead-acid battery takes approximate 18 hours.
4. Unplug charger from wall outlet and unclip battery from charger when charging is complete. Never disconnect charger from battery by pulling on the wires.

Model: MB-3527

